

VDS BASIC LOFT TELEPHONE

**Reference:** 03390

Audio terminal. Installed in homes, enables communication with outdoor panel and door opening.

DESCRIPTION

Audio terminal. Installed in homes, enables communication with outdoor panel and door opening.

A new telephone concept for the home. Integrated design, in line with new trends and lifestyles, simple and functional, combining quality and design.

Purity of line, technology and performance make this equipment an elegant and perfect element for any home.

Made in high impact ABS plastic, with a textured finish for easy cleaning and ultraviolet protection for greater resistance to sunlight.

Easy to fit wall mounted installation.

VDS system:

Simplified installation audio and video door entry system that does not use house call wires. The call is made by transmission of a digital call code generated by the VDS amplifier.

- In new works, installation can be carried out with the following type of wiring: UTP CAT5 / 5 wire / 3 wire + Coaxial (video).

Lets you manage up to 199 homes, 2 entrance accesses and a central guard unit.

Maximum distance from first access to last home: 200 m.

- In replacement works, the change from analogue entry to video entry system can be done taking advantage of the existing wiring.

The system capacity and distance will depend on the installation wiring.

VDS amplifier comes with voice synthesizer as standard issue.

When the door release is activated a message is heard: "Door open, please close after entering".

The home terminals require simple programming done from the outdoor panel. By means of this programming a call code is assigned to each terminal (telephone or monitor).

Communication is private.

Wiring. Audio: 3-wire bus. Video: UTP CAT5 / 5 wire / 3 wire + Coaxial (video).

Maximum distance from first access to last home: 200 m.

TECHNICAL SPECIFICATIONS

Terminal has a built-in magnet in the earpiece area that ensures the arm is well fitted and fixed to the base.

This prevents the arm falling off damaging the wall when hanging up and also avoids faults caused in the installation by being badly hung.

FERMAX

Screw-on surface assembly.

Power supply: 18 Vdc

Door release and guard unit call button.

Door bell: for direct house call button connection to monitor/telephone.

Private communication. Conversation secrecy.

Consumption:

- in standby: 5 mA.

- in call 220 mA

- active: 15 mA

Weight: 0,2853 kg

Size of product when packed: 25,8x8,8x5,8 cm

EAN 13: 8424299033907

FERMAX

ABN:96 059 925 692



FERMVISION

RISCO GROUP

EGi

CROSS POINT Guardall



smile by FERMAX

i:
product
design award
2014

Audio, Video and IP Intercoms
Access Control
Sound Distribution
Security Intruder Alarms
CCTV and IP Cameras
Residential
Commercial
Security Consultancy

NSW

U1, 37-39 Green St,
Banksmeadow, NSW. 2019
p. 61 2 9700 1700
f. 61 2 9700 1955
sales@fermaxaus.com.au

QLD

U11, 8 Fortitude Cres,
Burleigh Heads, QLD. 4220
p. 61 7 5520 2266
f. 61 7 5520 4591
qld@fermaxaus.com.au

VIC

U30, 640-680 Geelong Rd,
Brooklyn, VIC. 3012
p. 61 3 9314 2220
f. 61 3 9314 7772
vic@fermaxaus.com.au

WA

PO Box 587
Balcatta. 6914
m. 0438 700 101
wa@fermaxaus.com.au

fermaxaus

